

 **JV-1010**
64-VOICE SYNTHESIZER MODULE

TURBOSTART

*** JV-1010 TURBO FACTS ***

The JV-1010 64-Voice Synthesizer Module is a half rackspace sound module that features the full sound set of the JV-1080/2080 synth modules. It also includes the sounds from the Session wave expansion board, and a slot for installing an additional SR-JV80 Series expansion board of your choice. Features include:

- Compact half-rackspace, expandable synth module with 64-voice polyphony
- Includes the complete sound set of the JV-1080/2080 sound modules, plus the sounds from the "Session" expansion board (1023 Patches before expansion)
- Expansion slot for installing one of sixteen additional SR-JV80 Series Wave Expansion boards
- Intuitive knob-style control and straightforward interface
- Dedicated reverb and chorus effects, plus 40 built-in EFX algorithms such as distortion and rotary simulation
- Phrase Preview button and Category Bank Select knob make it easy to find the Patches you want
- General MIDI compatible
- Includes Emagic® SoundDiver™ software for Patch editing

• **Initialize**

This function resets the settings of the Patch, Performance, and Rhythm Sets to the factory default settings. Use the following procedure to initialize the JV-1010:

- 1) Press VALUE knob to switch to a mode other than the Patch mode.
- 2) Hold down the VOLUME knob and press the VALUE knob.
- 3) Turn the CATEGORY/BANK knob to select "PIANO(Factory Reset)."
- 4) Press the VALUE knob to display "Sur."
- 5) Press the VALUE knob to initialize the JV-1010.

• **Playing the Demo Songs**

The JV-1010 contains 4 demo songs that demonstrate the internal sounds and effects. Use the following procedure to listen to the demo songs:

- 1) Turn the CATEGORY/BANK knob to select DEMO.
- 2) Turn the VALUE knob to select the desired song.
- 3) Press the VALUE knob or the VOLUME knob start demo song playback. Press either knob again to stop playback.

• **Selecting Patches**

The JV-1010 contains over 1,000 built-in sounds. Use the following procedure to select a Patch:

- 1) Press the VALUE knob to select Patch mode (PATCH).
- 2) Turn the CATEGORY/BANK knob to select the desired bank.
- 3) Turn the VALUE knob to select the desired Patch.

(Try these Patches: User: No. 017 Adrenaline, Preset-A: No. 023 PsychoRhodes, Preset-B: No. 052 Blade Racer, Preset-E: No. 095 Dimensional, Session: No. 182 DCO Sweeper.)

• **Using the Category Function**

The Category function allows you to search for Patches based on instrument type. Use the following procedure to select a Patch by Category:

- 1) Press the VALUE knob to select Patch mode (PATCH).
- 2) Turn the CATEGORY/BANK knob to select a category.
- 3) Turn the VALUE knob to select the desired Patch.

• **Auditioning Patches (Phrase Preview)**

The Phrase Preview function allows you to audition sounds at the touch of a button. A short sample of the selected Patch is played in a style associated with that sound. Use the following procedure to try the Phrase Preview function:

- 1) Press the VALUE knob to select the Patch mode.
- 2) Turn the CATEGORY/BANK knob to select "Session."
- 3) Turn the VALUE knob to select "023."
- 4) Hold down the VOLUME knob to hear the selected Patch.

• **Using the JV-1010 as a GM Module**

The JV-1010 features a GM mode which provides a convenient way to playback or create GM compatible files. Use the following procedure to place the JV-1010 into GM mode:

- 1) Press the VALUE knob repeatedly to select "GM."

• **Configuring the JV-1010 with SoundDiver**

A copy of Emagic's SoundDiver is included for Patch editing on the JV-1010. This software allows you to quickly and easily edit the parameters of the JV-1010 from your Mac or PC. Before you can do this, it is necessary to configure the JV-1010 for use with your computer. First, you will need to connect the proper cable (for PC use RSC-15AT, for Mac use RSC-15APL) to the serial port on your computer. Or, if you already have a MIDI interface, connect the MIDI ports on the JV-1010 to your interface. Make sure the power for the JV-1010, the computer, and any additional devices is turned off and use the following procedure to configure the JV-1010 for use with SoundDiver:

For PC:

- 1) Connect a RSC-15AT serial cable from the serial port of the JV-1010 to the computer's serial port (RS-232C).
- 2) Set the COMPUTER switch on the rear panel to "PC-2."
- 3) Turn the power for all devices on.

For Mac:

- 1) Connect a RSC-15APL serial cable from the serial port of the JV-1010 to the computer's serial port.
- 2) Set the COMPUTER switch on the rear panel to "Mac."
- 3) Turn the power for all devices on.

Use the following procedure when connecting with MIDI cables:

- 1) Set the COMPUTER switch on the rear panel to "MIDI."
- 2) Connect a MIDI cable from the JV-1010's MIDI OUT to the MIDI IN of the MIDI interface.
- 3) Connect a MIDI cable from the JV-1010's MIDI IN to the MIDI OUT of the MIDI interface.
- 4) Turn the power for all devices on.